

LH 2500 Art. 3988

D Betriebsanleitung
Leisehäcksler

GB Instructies voor gebruik
Quiet Shredder

F Mode d'emploi
Broyeur silencieux

NL Gebruiksaanwijzing
Hakselaar

S Bruksanvisning
Tystgående kompostkvarn

I Istruzioni per l'uso
Biotrituratore silenzioso

E Manual de instrucciones
Trituradora silenciosa

P Instruções de utilização
Triturador silencioso

DK Brugsanvisning
Lydsvag Kompostkværn

GARDENA Quiet Shredder LH 2500

Welcome to the Garden with GARDENA...



Translation of the original instructions from German. Please read these operating instructions carefully and observe the notes given. Use these operating instructions to familiarise yourself with the quiet shredder, its proper use and the notes on safety.



For safety reasons, children under the age of 16 and people not familiar with these operating instructions must not use this quiet shredder.

→ Please keep these operating instructions in a safe place.

Contents

| | |
|---|----|
| 1. Where to Use Your GARDENA Quiet Shredder | 9 |
| 2. Safety instructions | 9 |
| 3. Assembly | 11 |
| 4. Putting into Operation | 11 |
| 5. Maintenance | 12 |
| 6. Trouble-shooting | 13 |
| 7. Putting Out of Operation | 13 |
| 8. Technical Data | 14 |
| 9. Service | 14 |

1. Where to Use Your GARDENA Quiet Shredder

Intended Use

The GARDENA shredder is designed for cutting organic material e.g. plant waste, in domestic and hobby gardens.

Please note



The shredder is not suitable for preparing soil, for example, and must never be used to shred metal parts, stones, soil, glass, textiles, paper, cardboard or plastic. These materials will cause serious damage to the cutting tool. There is also the risk of injury from stones and other materials that are ejected from the shredder.

2. Safety instructions

→ Please read the notes on safety on the shredder.



Warning!

→ Please read the operating instructions before using the shredder.



Danger! Electric Shock!

→ Before maintenance, disconnect the plug from the mains!



Danger! Risk of injury!

→ Keep bystanders away!



Danger! Risk of injury!

→ Keep hands and feet out of openings while machine is running.




Danger! Risk of injury!

Risk of injury to eyes!
→ Wear eye and hearing protection!


Proper Use / Responsibility:**Danger! Risk of injury!****This shredder can cause serious injuries!****Rotating tool!****The tool does not stop immediately after you have turned off the motor!****Danger of trapping fingers!****Risk of injury! When the shredder is plugged in, never reach into the ejection shaft/feeding funnel.****Keep your face and body away from the feeding funnel.****Inspect the unit before each use.****Do not use the shredder if safety devices and/or the cutting device are damaged or worn. Never operate the unit with the safety devices by-passed or missing.****Never disable the safety devices.****Before starting the shredder, ensure that the feeding funnel is secured properly. Tighten the bolts if necessary.****You are responsible for the safety of the working area.****Stand the shredder on an even, sturdy and stable surface.****Familiarise yourself with the surroundings of your working area. Check for possible risks which might be not audible due to the noise of the machine.****Only use the shredder for the purposes specified in these instructions.****Make sure that there are no other people (especially children) or animals anywhere near the working area.****Do not wear loose clothing, jewellery etc. which could get trapped in the shredder.****Wear sturdy working shoes, long trousers, gloves as well as safety goggles and ear protection available from specialist dealers.****Ensure that you have a secure foothold when working.****To prevent damaging the shredder and to prevent fires starting, keep the ventilation slits of the motor free from particles of dirt.****The shredder must not be tilted or tipped when in operation.****If foreign bodies fall onto the blades or if unusual sounds or vibrations occur, unplug the mains plug immediately and wait until the blades have stopped moving.****Remove the obstacle. Check the shredder for any damage / loose parts and if necessary have your shredder repaired.****Electric Safety:****Danger! Electric Shock!****The shredder must only be operated with undamaged electric cable.****If the electric cable or the extension cable is damaged disconnect the mains plug immediately.****Check the power cable regularly for damage and signs of wear and tear.****The socket of an extension cable should be water-proof or the connection sockets for extension cables must be made of rubber or be encased in rubber according to DIN VDE 0620.****Only use permitted extension cables. Ask your electrician.****Extension cable:****< 35 m / 1,5 mm² cross-section****< 100 m / 2,5 mm² cross-section****Power cables must not be of lower quality than the H05-RN-F rubber hose lines.****We recommend using a circuit breaker with a rated residual current of ≤ 30 mA.****In Switzerland use of a residual-current device is obligatory.****Keep the mains cable away from the filling and ejection funnels.****If a voltage outage occurs, the shredder is disconnected from the mains power by an undervoltage relay. The shredder must therefore be restarted once the mains voltage supply is restored.*****Interruptions of Work / Environment:*****Never leave the shredder unattended at the working area. If you interrupt your work store the unit in a safe place.****Before moving the shredder to a different place, always switch off the motor, unplug the mains plug, and wait until the blades have stopped moving.****Never use the unit when it is raining or in damp or wet areas.****Do not operate your shredder near swimming pools or garden ponds.****Please observe the prescribed local quiet times.**

3. Assembly

Assembling the Trolley:




1. Stand the shredder on the feeding funnel ①.
2. Unscrew the 4 M6 nuts ② and remove the transport lock ③.
The transport lock must be kept for transporting without the trolley.
3. Push 2 round-head bolts M6 x 55 ⑥ through the holes in the trolley ④ and mount the wheel axle ⑦.
4. Fit a washer (\varnothing 6 mm) ⑤ on each of the 2 round-head bolts ⑥ and secure the wheel axle ⑦ using 2 M6 nuts ②.
5. Insert the bolts ⑧ through the wheels ⑨, slide on the serrated lock washers (\varnothing 8 mm) ⑩ and tighten the bolts ⑧ in the wheel axle ⑦.
6. Push the wheel caps ⑪ onto the wheels ⑨.
7. Fit the trolley ④ on the feeding funnel ①.
8. Fit a washer \varnothing 6 mm ⑤ onto each of the 4 bolts and secure the trolley ④ with 4 M6 nuts ②.



GB

4. Putting into Operation

Shredding:




Danger! Risk of injury!
→ Always wear gloves, eye protection and ear protection when operating your shredder.

Switching On the Shredder:

Make sure the feeding funnel is empty before you switch on the shredder.

1. Lift up strain relief clamp ⑫ and plug the mains power extension cable into the shredder socket.
2. Plug mains power extension cable into a mains socket.
3. Press the lock ⑭ and turn the switch ⑮ to the **Forwards ↗** position.
4. Press the green **ON** switch ⑯.

You may notice a clicking sound when you switch on your shredder above all when your shredder is new. This noise is caused by the designed position of the counter-roller of the cutting cylinder and is completely normal. The noise will diminish to a minimum over time.




Switching Off the Shredder:

The cutting blades continue to move for a few seconds after you switch off the shredder.


Do not turn off the motor until the shredder is completely empty otherwise it may be difficult to turn the shredder on again.

→ Press the red **OFF** switch ⑯.

Reversing the Direction of Rotation:



Anti-Blocking Device:



Shredding tips:

If the material you are shredding becomes jammed in the cutting cylinder, you can reverse the direction of rotation to release the material.


1. Press the red **OFF** switch ⑯ and wait until the cutting cylinder stops moving.
2. Press the lock ⑭ and turn the switch ⑮ to the **Backwards position** ⚡. *The switch ⑮ can only be turned when the lock ⑭ is pressed.*
3. Press the green **ON** switch ⑯.

If the cutting cylinder suddenly becomes blocked (e.g. due to a foreign object or feeding in too much material or branches that are too thick), the cutting cylinder direction of rotation normally switches automatically to "Backwards" to release the trapped material. The switch remains in the "Forwards" position.

1. Press the red **OFF** switch ⑯ and wait until the cutting cylinder stops moving.
The cutting cylinder direction of rotation is automatically changed back to "Forwards".
2. Press the green **ON** switch ⑯.

5. Maintenance

Cleaning the Shredder:



Danger! Risk of injury!

- Always switch off the motor and wait for the cylinder to stop moving before carrying out maintenance work, unplug the mains plug, and wear protective gloves.
- To avoid injury to persons and property, never clean your shredder under running water, in particular not with water under high pressure.

Always keep the ventilation slit ⑯ free of dirt.

- Remove dirt and shredded material using a soft brush or cloth straight away after you have finished shredding.

6. Trouble-shooting

GB



Danger! Risk of injury!

- When carrying out maintenance work, always switch off the motor, wait for the cutting blades to stop moving, unplug the mains plug, and wear protective gloves.

| Problem | Possible cause | Remedy |
|--|---|--|
| Motor does not start | No mains voltage because fuse is defective. | → Install new fuse. |
| | Power cable defective | → Check power cable / replace power cable. |
| Motor switches off | Blockage protection activated due to constant overload or blockage at the cylinder. | → After waiting until the cooling-down time has elapsed, the motor can be restarted. |
| Shredder does not draw shredding material in | Blockage due to too soft shredding material. | Add harder branches. |
| | Cutting cylinder rotating backwards. | → Reverse the direction of rotation. |
| | Collection container over-full (cylinder blocked). | → Empty the collection container. |
| Direction of rotation changes automatically | Shredder blocked by shredded material. | → Switch off the shredder and wait until cylinder has stopped moving. Switch the shredder back on. |
| Shredded material is not cut all the way through and strands remain joined like a chain | Cutting cylinder worn or damaged. | → Cutting cylinder must be replaced by GARDENA Service or an authorised specialist. |

If any other faults occur, please contact GARDENA Service.



Repairs to the electrical component and replacement of the cutting cylinder and counter-roller must only be carried out by GARDENA Service or an authorised specialist dealer.

7. Putting Out of Operation

Storing Your Shredder:

- Store your shredder in a dry place out of the reach of children.

Disposal:

(in accordance with
RL 2002/96/EC)



Product must not be added to normal household refuse but must be disposed of properly.

8. Technical Data

| LH 2500 (Art. 3988) | |
|---|------------------------|
| Length / Width / Height | 63 cm / 50 cm / 100 cm |
| Weight | 25 kg |
| Power consumption | 2500 W |
| Voltage / Frequency | 230 V / 50 Hz |
| Fuse | 10 A slow blow |
| Nominal speed of cutting cylinder | 39 rpm |
| Branch diameter of dry wood | up to 40 mm |
| Branch diameter of soft wood | up to 44 mm |
| Working area related emission characteristic value L_{pA}¹⁾ | 82 dB (A) |
| Noise level L_{WA}¹⁾ | 96 dB (A) |

1) Measuring method according to RAL UZ 54

9. Service

Warranty

GARDENA guarantees this product for 2 years (from date of purchase). This guarantee covers all serious defects of the unit that can be proved to be material or manufacturing faults. Under warranty we will either replace the unit or repair it free of charge if the following conditions apply:

- The unit must have been handled properly and in keeping with the requirements of the operating instructions.
- Neither the purchaser nor a non-authorised third party have attempted to repair the unit.

The cutting cylinder and counter-roller are wearing parts and are therefore not covered by the warranty.

This manufacturer's guarantee does not affect the user's existing warranty claims against the dealer/seller.

If a fault occurs with your quiet shredder, please return the faulty unit together with the receipt and a description of the fault, with postage paid to the address of the Service Centre on the back of these operating instructions.

The transport lock must always be fitted when transporting without the trolley.

| | |
|--|---|
| D Produkthaftung | Wir weisen ausdrücklich darauf hin, dass wir nach dem Produkthaftungsgesetz nicht für durch unsere Geräte hervorgerufene Schäden einzustehen haben, sofern diese durch unsachgemäße Reparatur verursacht oder bei einem Teileaustausch nicht unsere Original GARDENA Teile oder von uns freigegebene Teile verwendet werden und die Reparatur nicht vom GARDENA Service oder dem autorisierten Fachmann durchgeführt wird. Entsprechendes gilt für Ergänzungsteile und Zubehör. |
| GB Product Liability | We expressly point out that, in accordance with the product liability law, we are not liable for any damage caused by our units if it is due to improper repair or if parts exchanged are not original GARDENA parts or parts approved by us, and, if the repairs were not carried out by a GARDENA Service Centre or an authorised specialist. The same applies to spare parts and accessories. |
| F Responsabilité | Nous vous signalons expressément que GARDENA n'est pas responsable des dommages causés par ses appareils, dans la mesure où ces dommages seraient causés suite à une réparation non conforme, dans la mesure où, lors d'un échange de pièces, les pièces d'origine GARDENA n'auraient pas été utilisées, ou si la réparation n'a pas été effectuée par le Service Après-Vente GARDENA ou l'un des Centres SAV agréés GARDENA. Ceci est également valable pour tout ajout de pièces et d'accessoires autres que ceux préconisés par GARDENA. |
| NL Productaansprakelijkheid | Wij wijzen er nadrukkelijk op, dat wij op grond van de wet aansprakelijkheid voor producten niet aansprakelijk zijn voor schade ontstaan door onze apparaten, indien deze door onvakkundige reparatie veroorzaakt zijn, of er bij het uitwisselen van onderdelen geen gebruik gemaakt werd van onze originele GARDENA onderdelen of door ons vrijegeven onderdelen en de reparatie niet door de GARDENA technische dienst of de bevoegde vakman uitgevoerd werd. Ditzelfde geldt voor extra-onderdelen en accessoires. |
| S Produktansvar | Tillverkaren är inte ansvarig för skada som orsakats av produkten om skadan beror på att produkten har reparerats felaktigt eller om, vid reparation eller utbytte, andra än Original GARDENA reservdelar har använts. Samma sak gäller för kompletteringsdelar och tillbehör. |
| I Responsabilità del prodotto | Si rende espressamente noto che, conformemente alla legislazione sulla responsabilità del prodotto, non si risponde di danni causati da nostri articoli se originati da riparazioni eseguite non correttamente o da sostituzioni di parti effettuate con materiale non originale GARDENA o comunque da noi non approvato e, in ogni caso, qualora l'intervento non venga eseguito da un centro assistenza GARDENA o da personale specializzato autorizzato. Lo stesso vale per le parti complementari e gli accessori. |
| E Responsabilidad de productos | Advertimos que conforme a la ley de responsabilidad de productos no nos responsabilizamos de daños causados por nuestros aparatos, siempre y cuando dichos daños hayan sido originados por arreglos o reparaciones indebidas, por cambios con piezas que no sean piezas originales GARDENA o bien piezas autorizadas por nosotros, así como en aquellos casos en que la reparación no haya sido efectuada por un Servicio Técnico GARDENA o por un técnico autorizado. Lo mismo es aplicable para las piezas complementarias y accesorios. |
| P Responsabilidade sobre o produto | Queremos salientar que segundo a lei da responsabilidade do fabricante, nós não nos responsabilizaremos por danos causados pelo nosso equipamento, quando estes ocorram em decorrência de reparações inadequadas ou da substituição de peças por peças não originais da GARDENA, ou peças não autorizadas. A responsabilidade tornar-se-á nula também depois de reparações realizadas por oficinas não autorizadas pela GARDENA. Esta restrição valerá também para peças adicionais e acessórios. |
| DK Produktansvar | Vi gør udtrykkeligt opmærksom på at i henhold til produktansvarsloven er vi ikke ansvarlige for skader forårsaget af vores udstyr, hvis det skyldes uautoriserede reparationer eller hvis dele er skiftet ud og der ikke er anvendt originale GARDENA dele eller dele godkendt af os, eller hvis reparationerne ikke er udført af GARDENA-service eller en autoriseret fagmand. Det samme gælder for ekstra udstyr og tilbehør. |

| | | |
|---|---|--|
| D EU-Konformitätserklärung MaschinenVerordnung (9. GSGVO) / EMVG / Niedersp. RL | Bezeichnung des Gerätes: Description of the unit: Désignation du matériel : Omschrijving van het apparaat: Produktbeskrivning: Descrizione del prodotto: Descripción de la mercancía: Descrição do aparelho: Beskrivelse af enhederne: | Leisehäckslar Quiet Shredder Broyeur silencieux Geruisloze hakselaar Tystgående kompostkvarn Biotritutatore silenzioso Trituradora silenciosa Triturador silencioso Lydsvag kompostkværn |
| GB EU Certificate of Conformity | Type: Type: Type: Typ: Typ: LH 2500 Modello: Tipo: Tipo: Type: | Art.-Nr.: Art. No.: Référence : Art. nr.: Art. nr.: 3988 Art. : Art. N°: Art. N°: Varenr. : |
| F Certificat de conformité aux directives européennes | EU-Richtlinien: EU directives: Directives européennes : EU-richtlijnen: EU direktiv: Directive UE: Normativa UE: Directrices da UE: EU Retningslinier: | 98/37/EC : 1998 2006/42/EC : 2006 2006/95/EC 2004/108/EC 2000/14/EC |
| NL EU-overeenstemmingsverklaring | Hinterlegte Dokumentation: Konformitätsbewertungsverfahren: Deposited Documentation: Conformity Assessment Procedure: Documentation déposée : Procédure d'évaluation de la conformité : | GARDENA Technische Dokumentation Nach 2000/14/EG Art. 14 Annex V GARDENA Technical Documentation according to 2000/14/EC Art. 14 Annex V Documentation technique GARDENA Selon 2000/14/CE art. 14 Annexe V |
| S EU Tillverkarintyg | Schall-Leistungspegel: Noise level: Puissance acoustique : Geluidsniveau: Ljudnivå: uppmätt / garantierad Livello rumorosità: Nivel sonoro: Nível de ruido: Lydtryksniveau: | gemessen / garantiert measured / guaranteed mesurée / garantie gemeten / gegarandeerd testato / garantito medido / garantizado medido / garantido afmålt / garanti |
| I Dichiarazione di conformità alle norme UE | 2500 W | 96 dB (A) / 98 dB (A) |
| E Declaración de conformidad de la UE | Anbringungsjahr der CE-Kennzeichnung: Year of CE marking: Date d'apposition du marquage CE : Installatiejaar van de CE-aanduiding: CE-Märkningsår: Anno di rilascio della certificazione CE: Colocación del distintivo CE: Ano de marcação pela CE: CE-Mærkningsår: | 2004 |
| P Certificado de conformidade da UE | Ulm, den 01.07.2004 Ulm, 01.07.2004 Fait à Ulm, le 01.07.2004 Ulm, 01-07-2004 Ulm, 2004.07.01. Ulm, 01.07.2004 Ulm, 01.07.2004 Ulm, 01.07.2004 Ulm, 01.07.2004 | Peter Lameli Technische Leitung Technical Dept. Manager Direction technique Hoofd technische dienst Technical Director Direzione Tecnica Dirección Técnica Director Técnico Teknisk direktør |
| DK EU Overensstemmelse certifikat | | |
| Undertecknade firma GARDENA International GmbH, Hans-Lorensen-Str. 40, D-89079 Ulm, intygar härmed att nedan nämnda produkter överensstämmer med EU:s direktiv, EU:s säkerhetsstandard och produktspecifikation. Detta intyg upphör att gälla om produkten ändras utan vårt tillstånd. | | |
| La sottoscritta GARDENA International GmbH, Hans-Lorensen-Str. 40, D-89079 Ulm, certifica che il prodotto qui di seguito indicato, nei modelli da noi commercializzati, è conforme alle direttive armonizzate UE nonché agli standard di sicurezza e agli standard specifici di prodotto. Qualunque modifica apportata al prodotto senza nostra specifica autorizzazione invalida la presente dichiarazione. | | |
| El que subscribe GARDENA International GmbH, Hans-Lorensen-Str. 40, D-89079 Ulm, declara que la presente mercancía, objeto de la presente declaración, cumple con todas las normas de la UE, en lo que a normas técnicas, de homologación y de seguridad se refiere. En caso de realizar cualquier modificación en la presente mercancía sin nuestra previa autorización, esta declaración pierde su validez. | | |
| Os abaixo mencionados GARDENA International GmbH, Hans-Lorensen-Str. 40, D-89079 Ulm, por este meio certificam que ao sair da fábrica o aparelho abaixo mencionado está de acordo com as directrizes harmonizadas da UE, padrões de segurança e de produtos específicos. Este certificado ficará nulo se a unidade for modificada sem a nossa aprovação. | | |
| Undertegnede GARDENA International GmbH, Hans-Lorensen-Str. 40, D-89079 Ulm bekræfter hermed, at enhederne listet herunder, ved afsendelse fra fabrikken, er i overensstemmelse med harmoniserede EU retningslinier, EU sikkerhedsstandarde og produktspecifikationsstandarde. Dette certifikat træder ud af kraft hvis enhederne er ændret uden vor godkendelse. | | |

| | | | |
|--|--|---|--|
| Deutschland / Germany GARDENA Manufacturing GmbH Service Center Hans-Lorenser-Straße 40 D-89079 Ulm Produktfragen: (+49) 731 490-123 Reparaturen: (+49) 731 490-290 service@gardena.com | Croatia KLIS d.o.o. Stanciceva 79 10419 Vukovina Phone: (+385) 1 622 7770 gardena@klis-trgovina.hr | Italy GARDENA Italia S.p.A. Via Donizetti 22 20020 Lainate (Mi) Phone: (+39) 02.93.94.79.1 info@gardenaitalia.it | Singapore Hy - Ray PRIVATE LIMITED 40 Jalan Pemimpin #02-08 Tat Ann Building Singapore 577185 Phone: (+65) 6253 2277 hyray@singnet.com.sg |
| Argentina Argensem® S.A. Calle Colonia Japonesa s/n (1625) Loma Verde Escobar, Buenos Aires Phone: (+54) 34 88 49 40 40 info@argensem.com.ar | Cyprus FARMOKIPIKI LTD P.O. Box 7098 74, Digeni Akrita Ave. 1641 Nicosia Phone: (+357) 22 75 47 62 condam@spidernet.com.cy | Japan KAKUICHI Co. Ltd. Sumitomo Realty & Development Kojimachi BLDG., 8F 5-1 Nibanncyo, Chiyoda-ku Tokyo 100-0084 Phone: (+81) 33 264 4721 m_ishihara@kaku-ichi.co.jp | Slovak Republic GARDENA Slovensko, s.r.o. Panónska cesta 17 851 04 Bratislava Phone: (+421) 263 453 722 info@gardena.sk |
| Australia Nylex Consumer Products 50-70 Stanley Drive Somerton, Victoria, 3062 Phone: (+61) 1800 658 276 spare.parts@nylex.com.au | Czech Republic GARDENA spol. s r.o. Řípská 20a, č.p. 1153 627 00 Brno Phone: (+420) 800 100 425 gardena@gardenabrn.cz | Luxembourg Magasins Jules Neuberg 39, rue Jacques Stas Luxembourg-Gasperich 2549 Case Postale No. 12 Luxembourg 2010 Phone: (+352) 40 14 01 api@neuberg.lu | Slovenia GARDENA d.o.o. Brodisce 15 1236 Trzin Phone: (+386) 1 580 93 32 servis@gardena.si |
| Austria / Österreich GARDENA Österreich Ges.m.b.H. Stettnerweg 11-15 2100 Korneuburg Tel.: (+43) 22 62 7 45 45 36 kundendienst@gardena.at | Denmark GARDENA Norden AB Salgsafdeling Danmark Box 9003 S-200 39 Malmö info@gardena.dk | Netherlands GARDENA Nederland B.V. Postbus 50176 1305 AD ALMERE Phone: (+31) 36 521 00 00 info@gardena.nl | South Africa GARDENA South Africa (Pty) Ltd. P.O. Box 11534 Vorna Valley 1686 Phone: (+27) 11 315 02 23 sales@gardena.co.za |
| Belgium GARDENA Belgium NV/SA Sterrebeekstraat 163 1930 Zaventem Phone: (+32) 2 7 20 92 12 Mail: info@gardena.be | Finland Habitec Oy Martinkyläntie 52 01720 Vantaa | Neth. Antilles GARDENA PARIS NORD 2 69, rue de la Belle Etoile BP 57080 ROISSY EN FRANCE 95948 ROISSY CDG CEDEX Tél. (+33) 0826 101 455 service.consommateurs@ gardena.fr | Spain GARDENA IBÉRICA S.L.U. C / Basauri, nº 6 La Florida 28023 Madrid Phone: (+34) 91 708 05 00 atencioncliente@gardena.es |
| Brazil Palash Comércio e Importação Ltda. Rua Américo Brasiliense, 2414 - Chácara Sto Antônio São Paulo - SP - Brasil - CEP 04715-005 Phone: (+55) 11 5181-0909 eduardo@palash.com.br | Great Britain GARDENA UK Ltd. 27-28 Brenkley Way Bleazerd Business Park Seaton Burn Newcastle upon Tyne NE13 6DS info@gardena.co.uk | New Zealand NYLEX New Zealand Limited Building 2, 118 Savill Drive Mangere, Auckland Phone: (+64) 0800 22 00 88 spare.parts@nylex.com.au | Sweden GARDENA Norden AB Försäljningskontor Sverige Box 9003 200 39 Malmö info@gardena.se |
| Bulgaria DENEX LTD. 2 Luis Ahalier Str. - 7th floor Sofia 1404 Phone: (+359) 2 958 18 21 office@denex-bg.com | Greece Agrokip Psomadopoulos S.A. Ifaioustou 33A Industrial Area Koropi 194 00 Athens Greece V.A.T. EL093474846 Phone: (+30) 210 66 20 225 service@agrokip.gr | Norway GARDENA Norden AB Salgskontor Norge Karihuageveien 89 1086 Oslo info@gardena.no | Switzerland / Schweiz GARDENA (Schweiz) AG Bitzberg 1 8184 Bachenbülach Phone: (+41) 848 800 464 info@gardena.ch |
| Canada GARDENA Canada Ltd. 100 Summerlea Road Brampton, Ontario L6T 4X3 Phone: (+1) 905 792 93 30 info@gardenacanada.com | Portugal GARDENA Portugal Lda. Recta da Granja do Marquês Edif. GARDENA Algueirão 2725-596 Mem Martins Phone: (+351) 21 922 85 30 info@gardena.pt | Turkey GARDENA / Dost Dış Ticaret Mümessilik A.Ş. Sanayi Çad. Adil Sokak No. 1 Kartal - İstanbul Phone: (+90) 216 38 93 939 info@gardena-dost.com.tr | Ukraine / Украина ALTTEST JSC 4 Petropavlivska Street Petropavlivska Borschahivka Town Kyivo Svyatoslyny Region 08130, Ukraine Phone: (+380) 44 459 57 03 upy@alttest.kiev.ua |
| Chile Antonio Martinic y Cia Ltda. Cassillas 272 Centro de Cassillas Santiago de Chile Phone: (+56) 2 20 10 708 garfar_cl@yahoo.com | Hungary GARDENA Magyarország Kft. Késmárki utca 22 1158 Budapest Phone: (+36) 80 20 40 33 gardena@gardena.hu | Romania MADEX INTERNATIONAL SRL Soseaua Odaii 117-123, Sector 1, Bucureşti, RO 013603 Phone: (+40) 21 352 76 03 madex@ines.ro | USA Melnor Inc. 3085 Shawnee Drive Winchester, VA 22604 Phone: (+1) 540 722-9080 service_us@melnor.com |
| Costa Rica Compania Exim Euroiberoamericana S.A. Los Colegios, Moravia, 200 metros al Sur del Colegio Saint Francis - San José Phone: (+506) 297 68 83 exim_euro@racsa.co.cr | Iceland Ó. Johnson & Kaaber Tunguhalsi 1 110 Reykjavík oqj@ojk.is | Russia / Россия ООО ГАРДЕНА РУС 123007, г. Москва Хорошевское шоссе, д. 32A Тел.: (+7) 495 647 25 10 info@gardena-rus.ru | 3988-20.960.03/0507 © GARDENA Manufacturing GmbH D-89070 Ulm http://www.gardena.com |